PC AVR Series Features:

- USB Quick Charging
- / Compact Design for Personal Use
- ✓ Protect the Tablets and Smart Phone
- √ 5 Ports USB / 5V total current 4A(2.4A/port max.)
- ✓ Built-in AVR





Power Center AVR Series

MODEL		PC AVR 4NEMA	PC AVR 8NEMA
DESCRIPTION		Power Center and Automatic Voltage Regulator	
CAPACITY	VA / Watts	1200VA 600W	
INPUT	Nominal Voltage	120VAC / 230 VAC Systems	
	Voltage Range	85 ~ 145VAC or 175~285VAC	
	Frequency	50 / 60Hz	
ОИТРИТ	Voltage	98 ~ 132VAC or 198~253VAC	
	Frequency	Same as Input	
	Built-In AVR	Single Boost & Buck	Pure Boost & Buck
	AC Socket	NEMA * 4pcs	NEMA * 8pcs
	USB Charger 5 Port	5V Total Current 4A/6A (2.4A/port Max.)	
OVER LOAD PROTECTOR	Breaker	ON/Off Switch and Power Safety Shut Down	
LED	On / Off	Green	Green
	Boost / Buck	X	Yellow
ENVIRONMENT	Temperature	0°C ~ 45°C	
	Humidity range	< 90% (Non-Condensing)	
	Audible Noise	< 40dB at 1 meter	
DIMENSIONS	D x W x H (cm)	207*134*93mm	

^{*} Specification Subject to Change without Prior Notice.